

**Amendments to the Claims:**

A listing of the entire set of pending claims (including amendments to the claims, if any) is submitted herewith per 37 CFR 1.121. This listing of claims will replace all prior versions, and listings, of claims in the application.

**Listing of Claims:**

1. (Currently Amended) A receiver (20) for optical communications including:

at least one primary optical detector (12) for receiving radiation from a radiation beam (16a) when the radiation beam is aligned with the primary optical detector (12), and

at least one auxiliary optical detector (15a) and at least one other auxiliary optical detector (15b) arranged to receive radiation from the radiation beam (16b) when the radiation beam is not aligned with the primary optical detector (12),

wherein the at least one auxiliary optical detector (15a) and the at least one other auxiliary optical detector (15b) are physically separated from each other by an air gap, and

wherein said at least two auxiliary optical detectors (15a, 15b) are positioned in front of a diffuser (13:71).

wherein the ~~receiver (20) further includes a~~ diffuser (13; 71) ~~[[encircling]]~~ encircles the at least one primary optical detector (12) to form an assembly (12, 13:71) that is arranged such that the diffuser (13:71) lies substantially in or close to the field of focus of a focusing element (11:70) for generating diffuse light by diffusely redirecting radiation intended for the at least one primary optical detector directly towards the ~~at least one auxiliary detector~~ auxiliary optical detectors (15a, 15b) in the case where the radiation beam is not aligned with the at least one primary optical detector.

2. (Previously Presented) A receiver according to claim 1 wherein the focusing element (11; 70) is used for focusing the incoming radiation beam (16b) onto the primary optical detector and/or the diffuser.

3. (Original) A receiver according to claim 2 including a receiver system (21) for retrieving data from redirected radiation received at the auxiliary detector.

4. (Previously Presented) A receiver according to claim 1 wherein the diffuser is a reflector and is arranged to face substantially in the same direction as the primary detector to reflect incoming radiation not aligned with the primary detector, and the auxiliary detector is arranged to substantially face the diffuser.
5. (Original) A receiver according to claim 4 wherein the diffuser is arranged in substantially the same plane as the primary detector, and the diffuser and primary detector are positioned in or in proximity to the focal plane of the focusing element.
6. (Original) A receiver according to claim 2 including a control system (22, 23) connected to the auxiliary detector for aligning the primary detector with respect to the radiation beam in at least one direction based on the intensity of radiation received at the auxiliary detector.
7. (Original) A receiver according to claim 6 wherein the control system aligns the primary detector with the radiation beam by moving the primary detector.
8. (Previously Presented) A receiver according to claim 6 further including a redirecting element arranged in the path of the incoming beam, wherein the control system aligns the primary detector with the radiation beam by moving the element.
9. (Previously Presented) A receiver according to claim 1 including at least one pair of auxiliary detectors (15a, 15b), each auxiliary detector being arranged to output current dependent on the intensity of received radiation, and the receiver includes means for calculating misalignment of the primary detector with respect to the radiation beam based on the output signals of each auxiliary detector (15a, 15b).
10. (Original) A receiver according to claim 9 including two pairs of auxiliary detectors, wherein the calculating means is connected to both pairs of detectors for calculating misalignment of the primary detector with respect to the radiation beam in two substantially perpendicular directions.

11. (Currently Amended) An optical network including a plurality of nodes, a first said node including a receiver ~~according to any preceding claim~~ and a second said node including a transmitter for transmitting a radiation beam to be received by said receiver, wherein the receiver (20) further includes a diffuser (13; 71) encircling at least one primary optical detector (12) to form an assembly (12, 13;71) that is arranged such that the diffuser (13;71) lies substantially in or close to the field of focus of a focusing element (11;70) for generating diffuse light by diffusely redirecting radiation intended for the at least one primary optical detector towards the at least one auxiliary detector in the case where the radiation beam is not aligned with the at least one primary optical detector.

12. (Original) An optical network according to claim 11, said first node including both a transmitter for transmitting a radiation beam and a receiver and said second node including a receiver, wherein the first node is arranged to align the radiation beam output from the transmitter on the first node with respect to the receiver on the second node, based on a signal output from the receiver in said first node.

13. (Previously Presented) An optical network according to claim 11 wherein the second node is arranged to transmit a relatively narrow divergence data beam and relatively wide divergence auxiliary beam, and wherein the receiver in the first node is arranged to align the primary detector with respect to the auxiliary radiation beam.

14. (Original) An optical network according to claim 13 wherein the network is arranged such that aligning the primary detector with respect to the auxiliary radiation beam also aligns the primary detector with the data beam from the second node.

15. (Currently Amended) A receiver (20) for optical communications including:  
at least one primary optical detector (12) for receiving an incoming radiation beam,  
  
a redirecting surface (13) for redirecting an incoming radiation beam (16b),  
at least one pair of auxiliary optical detectors (15a, 15b) arranged to receive

redirected radiation from the surface (13), and

a control system connected to the auxiliary detectors (15a, 15b) for aligning the primary detector (12) and the incoming radiation beam (16b) in at least one direction,

wherein the surface (13) is a diffuser (13; 71) encircling the at least one primary optical detector (12) to form an assembly (12, 13;71) that is arranged such that the diffuser (13;71) lies substantially in or close to the field of focus of a focusing element (11;70) for generating diffuse light by diffusely redirecting radiation intended for the at least one primary detector (12) towards the at least one pair of auxiliary optical detectors (15a, 15b) in the case where the radiation beam is not aligned with the at least one primary detector (12) and the control system aligns the primary detector (12) and radiation beam (16b) based on the intensity of redirected radiation received at the at least one pair of auxiliary optical detectors (15a, 15b) ~~auxiliary detectors (15a, 15b).~~